

9 5: .> // x z 9 [ħ Å 1 9 ~ ož

Low dropout linear regulator in a SOT23-3 Plastic Package .

< z² Å W • v y ['
 < ŷ ß v y S '
 < z 9 [y S < & S ' < 5 ; : # <
 < ä □ † y r
 < ä > ò A y J (& Q . `
 < z ŷ ß ™ Ò y [< 8 3 9 g . ` d Q . ` h
 < ß) ŷ μ ħ Å y ŷ ß ħ ú 9 Á € •
 < Ä å v ' ò k ? è '
 < ½ '
 < —) í D }

9 _ • > — Õ k * ' — Õ k ° È y , È — Õ ož

For use in power equipment, Communication equipment, Audio and video equipment.

–	d f		–	d f	
---	-----	--	---	-----	--

@ f	... Z	f >	% y
$\ddot{y} \mu \ 9$	V_{IN}	-0.3 to 40	V
$\ddot{y} \beta \ v$	I_{OUT}	200	mA
$\hat{o} \bullet \ \ddot{a}$	P_D	0.6	W
$\yen \ " \ \dagger$	T_{stg}	-40 to +125	°C
$W \bullet \ " \ \dagger$	T_A	-40 to +85	
' D N " \dagger g 10s h	T_{sold}	260	°C
$\dots^2 \ \wedge \prime$	HBM	2	kV
	MM	200	V

h y ò ç ~ ^ g Ú ^ Ý _ ¾ Ú ^ Â Ý Ì > k U + ~ ^ - è K ! Â C ° o ž @ f N © g

Ú ^ â Ý > k é [• ~ ^ " ¥ • 8 8 Ò go ž ò ç ~ ^ x ž • W • " Í + Â Ý â ' Ú ^ k ž

I Â U k i ñ § € o ž

Notes: If the device operating conditions over the maximum rating of the above-mentioned conditions, may cause permanent damage to the device. The above parameters is only part of the operating conditions the maximum, we do not recommend the device running outside the scope of this specification. If the device to work long hours under the condition of absolute maximum limit, its stability may be affected.

@ f	... Z	y i Ú ^	Â 4 >	Á ° >	Â Ý >	% y
$\ddot{y} \mu \ 9$	V_{IN}				36	V
$\ddot{y} \beta \ 9 \ g^1 h$	$V_{OUT \ g E h}$	$I_{OUT}=10mA$	4.9	5.0	5.1	V
$\ddot{y} \mu \ \ddot{y} \beta \ 9 [\ g^2 h$	V_{dif}	$I_{OUT}=100mA$ $V_{OUT}=5.0V$		450		mV
$^2 \ \hat{A} \ W \bullet \ v$	I_{SS}	$I_{OUT}=0mA$		2	5	uA
$\grave{c} \acute{u}^2 \dots \ddot{a}$	$\text{, } V_{load}$	$V_{IN}=V_{OUT \ AS \ A}+2V$ $1mA \ 0 \ I_{OUT} \ 0 \ 200mA$		20	50	mV
$\grave{c} \ \hat{A}^2 \dots \ddot{a}$	$\text{, } V_{line}$	$I_{OUT}=10mA$ $V_{OUT \ AS \ A}+2V \ 0 \ V_{IN} \ 0$ 36V		10	50	mV
$\ddot{y} \beta \ 9 \ " \ \dagger \ © \ f$	$\text{, } V_{OUT}/$ $(\text{, } T_A \cdot V_{OUT})$	$I_{OUT}=10mA$ -40 0 T_A 085 $V_{OUT}=0.5 \times$		50		ppm/
$\ddot{y} \beta \ v \ ' \grave{o}$	I_{LIM}					

@ f	... Z	y i Ú ^	Â 4 >	Á ° >	Â Ý >	% y
> ¼ f ò A	PSRR	IOUT=50mA Èf=100Hz		80		dB
		IOUT=50mA Èf=1kHz		70		
		IOUT=50mA Èf=10kHz		60		
		IOUT=50mA Èf=100kHz		50		
ÿ ß ™ Ò 9	VON	BW=10Hz to 100kHz		90		uVRMS

(1) VOUT

Ô ? d • Ž ¢ / Electrical Characteristic Curve

À¹€ĐÔ· / Typical Application Circuit

ÂÎ• / Basic Application

ÿßÝ v 9²-~ / High Output Current Voltage Regulator

?è‘• / Short-Circuit Protection

BRCO7550HMC

, M y f / Marking Instructions

7550H

^a ¢ y
7550H y ° Z W A
 y ÿ D Z W A k š ÿ D Z J

Note:
7550H: Product Type Code
****: Lot No. Code, code change with Lot No

